# CT140 PC Cooling Fan

2 Pack





#### Thermaltake CT140 PC Cooling Fan 2Pack

#### • Featuers

- Cable Integrated Daisy-chain Design with better cable management
- PWM Controlled Fan with a maximum speed of 1500 RPM
- Specifically tuned fan blade allows the air to be pushed further
- Optimized hydraulic bearing for reliable and silent operation
- Anti-vibration Mounting System Embedded

#### Specification

2 Pack

P/N	CL-F148-PL14BL-A
Fan Dimension	140 x 140 x 25 mm
Started Voltage	5 V
Rated Voltage	12 V
Rated Current	0.17 A (one fan)
Power Input	2.04 W (one fan)
Fan Speed	PWM 500~1500 R.P.M
Max. Air Pressure.	2.3 mm-H2O
Max. Air Flow.	77.37 CFM
Noise Level.	30.5 dB-A
BeaRiing Type	Hydraulic Bearing
Life expectation	40,000 hrs,25℃
Connector	4 PIN PWM
Note	PWM Cable x 2

#### Thermaltake CT140 PC Cooling Fan 2Pack

#### • Angle View



Front view



Back view







thermaltake

Side view



Parts
(M3 for Radiator x 8, T5x10 fan screw x 8
PWM extend cable x 2)

**Application** 

#### Thermaltake CT140 PC Cooling Fan 2Pack

### • Detail Features



#### **Daisy-chain Design**

better cable management



### Anti-vibration mounting system

Reduce vibrations between fan and chassis



#### **Application**

To provide the best cooling solution inside your chassis

# CT140 PC Cooling Fan

2 Pack



